

## **SECTION 26 24 16 - PANELBOARDS**

### **PART 1 - GENERAL**

#### **1.1 SUMMARY**

- A. This Section includes distribution panelboards and lighting and appliance branch-circuit panelboards.

#### **1.2 SUBMITTALS**

- A. Product Data: For each type of panelboard, overcurrent protective device, accessory, and component indicated. Include dimensions and manufacturers' technical data on features, performance, electrical characteristics, ratings, and finishes.
- B. Shop Drawings: For each panelboard and related equipment.
  - 1. Dimensioned plans, elevations, sections, and details. Verify space available meets NEC required working clearances. Show tabulations of installed devices, equipment features, and ratings. Include the following:
    - a. Enclosure types and details for types other than NEMA 250, Type 1.
    - b. Bus configuration, current, and voltage ratings.
    - c. Short-circuit current rating of panelboards and overcurrent protective devices.
    - d. Features, characteristics, ratings, and factory settings of individual overcurrent protective devices and auxiliary components.
  - 2. Wiring Diagrams: Power, signal, and control wiring.
  - 3. Field quality-control test reports.
  - 4. Operation and maintenance data.

#### **1.3 QUALITY ASSURANCE**

- A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- B. Source Limitations: Obtain panelboards, overcurrent protective devices, components, and accessories through one source from a single manufacturer.
- C. Comply with NEMA PB 1.
- D. Comply with NFPA 70.

#### 1.4 PROJECT CONDITIONS

- A. Interruption of electric service: Do not interrupt electric service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electric service according to requirements indicated:
  - 1. Notify Owners Representative no fewer than two weeks in advance of proposed interruption of electrical service.
  - 2. Do not proceed with interruption of electrical service without Owner's Representative's written permission.
- B. Source Limitations: Obtain panelboards, overcurrent protective devices, components, and

#### 1.5 COORDINATION

- A. Coordinate layout and installation of panelboards and components with other construction that penetrates walls or is supported by them, including electrical and other types of equipment, raceways, piping, and encumbrances to workspace clearance requirements.
- B. Coordinate size and location of concrete bases. Cast anchor-bolt inserts into bases. Concrete, reinforcement, and formwork requirements are specified in Division 03.
  - 1. Notify Owners Representative no fewer than two weeks in advance of proposed interruption of electrical service.

#### 1.6 EXTRA MATERIALS

- A. Furnish extra materials described below that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.
  - 1. Keys: Four spares for each type of panelboard cabinet lock.

### PART 2 - PRODUCTS

#### 2.1 MANUFACTURERS

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following :
  - 1. Panelboards, Overcurrent Protective Devices, Controllers, Contactors, and Accessories:
    - a. Eaton Corporation; Cutler Hammer Products
    - b. General Electric Co.; Electrical Distribution & Protection Div.
    - c. Siemens Energy & Automation, Inc.

## 2.2 MANUFACTURED UNITS

- A. Panel boards shall be front accessible, dead front type, door in door construction with lockable metal latch fasteners on all doors. Locks shall be keyed alike to match the existing keying system (Corbin Cabinet lock TEU-1 or GE-75).
- B. Enclosures: Surface mounted cabinets. NEMA PB 1, Type 1.
  - 1. Rated for environmental conditions at installed location.
    - a. Kitchen Areas: NEMA 250, Type 4X, stainless steel.
    - b. Other Wet or Damp Indoor Locations: NEMA 250, Type 4.
    - c. Hazardous Areas Indicated on Drawings: NEMA 250, Type 7C.
  - 2. Front: Secured to box with concealed trim clamps. For surface-mounted fronts, match box dimensions; for flush-mounted fronts, overlap box.
  - 3. Hinged Front Cover: Entire front trim hinged to box and with standard door within hinged trim cover. Front door and interior door shall each include keyed latches.
  - 4. Skirt for Surface-Mounted Panelboards: Same gage and finish as panelboard front with flanges for attachment to panelboard, wall, and ceiling or floor.
  - 5. Gutter Extension and Barrier: Same gage and finish as panelboard enclosure; integral with enclosure body. Arrange to isolate individual panel sections.
  - 6. Column-Type Panelboards: Narrow gutter extension, with cover, to overhead junction box equipped with ground and neutral terminal buses.
  - 7. Finish: Manufacturer's standard enamel finish over corrosion-resistant treatment or primer coat.
  - 8. Directory Card: With transparent protective cover, mounted in metal frame, inside panelboard door.
- C. Phase and Ground Buses:
  - 1. Material: Hard Drawn Copper.
  - 2. Equipment Ground Bus: Adequate for feeder and branch-circuit equipment ground conductors; bonded to box.
  - 3. Isolated Equipment Ground Bus: Adequate for branch-circuit equipment ground conductors; insulated from box.
  - 4. Extra-Capacity Neutral Bus: Neutral bus rated 200 percent of phase bus and UL listed as suitable for nonlinear loads.
  - 5. Split Bus: Vertical buses divided into individual vertical sections.
  - 6. All 208/120V panel boards shall be provided with a fully rated separate isolated ground bus to serve future computer loads.
- D. Conductor Connectors: Suitable for use with conductor material.
  - 1. Main and Neutral Lugs: Compression or Mechanical type.
  - 2. Ground Lugs and Bus Configured Terminators: Compression type.
  - 3. Feed-Through Lugs: Compression or Mechanical type suitable for use with conductor material. Locate at opposite end of bus from incoming lugs or main device.

- 4. Extra-Capacity Neutral Lugs: Rated 200 percent of phase lugs mounted on extra-capacity neutral bus.
- E. Service Equipment Label: UL labeled for use as service equipment for panelboards with main service disconnect switches.
- F. Future Devices: Mounting brackets, bus connections, and necessary appurtenances required for future installation of devices.
- G. Panelboards rated 400 amps and higher shall accept 225 amp branch circuit breakers.

#### 2.3 Panelboard Short-Circuit Rating:

- A. Panel Boards shall be fully rated for the available AIC. Series rated panel boards are not acceptable.
- B. Fully rated to interrupt symmetrical short-circuit current available at terminals as shown by the protective system device study.
  - 1. Minimum rating shall be as follows:
  - 2. 208Y/120V Panelboards      10,000AIC symmetrical
  - 3. 480Y/277V Panelboards      14,000AIC symmetrical
  - 4. Fusible Panelboards      100,000AIC symmetrical

#### 2.4 DISTRIBUTION PANELBOARDS

- A. Doors: Secured with vault-type latch with tumbler lock; keyed alike. Omit for fused-switch panelboards.
- B. Main Overcurrent Protective Devices: Circuit Breaker.
- C. Branch Overcurrent Protective Devices:
  - 1. Bolt on circuit breakers.
  - 2. Fused switches.
  - 3. Panel boards rated for 400 amps or above shall accept 225A frame circuit breakers.

#### 2.5 LIGHTING AND APPLIANCE BRANCH-CIRCUIT PANELBOARDS

- A. Branch Overcurrent Protective Devices: Bolt-on circuit breakers, replaceable without disturbing adjacent units.
- B. Panel boards shall be front accessible, dead front type, door in door construction with lockable metal latch fasteners on all doors. Locks shall be keyed alike to match the existing keying system.

## 2.6 OVERCURRENT PROTECTIVE DEVICES

- A. Molded-Case Circuit Breaker: UL 489, with interrupting capacity to meet available fault currents.
  - 1. Thermal-Magnetic Circuit Breakers: Inverse time-current element for low-level overloads, and instantaneous magnetic trip element for short circuits. Adjustable magnetic trip setting for circuit-breaker frame sizes 250 A and larger.
  - 2. Adjustable Instantaneous-Trip Circuit Breakers: Magnetic trip element with front-mounted, field-adjustable trip setting.
  - 3. Electronic trip-unit circuit breakers shall have RMS sensing; field-replaceable rating plug; and with the following field-adjustable settings:
    - a. Instantaneous trip.
    - b. Long- and short-time pickup levels.
    - c. Long- and short-time time adjustments.
    - d. Ground-fault pickup level, time delay, and I<sup>2</sup>t response.
  - 4. Current-Limiting Circuit Breakers: Frame sizes 400 A and smaller; let-through ratings less than NEMA FU 1, RK-5.
  - 5. Integrally Fused Circuit Breakers: Thermal-magnetic trip element with integral limiter-style fuse listed for use with circuit breaker; trip activation on fuse opening or on opening of fuse compartment door.
  - 6. GFCI Circuit Breakers: Single- and two-pole configurations with 30 -mA trip sensitivity.
  - 7. Molded-Case Circuit-Breaker Features and Accessories: Standard frame sizes, trip ratings, and number of poles.
    - a. Lugs: Mechanical or Compression style, suitable for number, size, trip ratings, and conductor materials.
    - b. Application Listing: Appropriate for application; Type SWD for switching fluorescent lighting loads; Type HACR for heating, air-conditioning, and refrigerating equipment.
    - c. Ground-Fault Protection: Integrally mounted relay and trip unit with adjustable pickup and time-delay settings, push-to-test feature, and ground-fault indicator.
    - d. Shunt Trip: 120-V trip coil energized from separate circuit, set to trip at 55 percent of rated voltage.
    - e. Multi-pole units enclosed in a single housing or factory-assembled to operate as a single unit.
- B. Fused Switch: NEMA KS 1, Type HD; clips to accommodate specified fuses; lockable handle.
- C. Fuses are specified in Division 26 Section "Fuses."

## 2.7 CONTROLLERS

- A. Motor Controllers: NEMA ICS 2, Class A, combination controller equipped for panelboard mounting and including the following accessories:
  - 1. Individual control-power transformers.
  - 2. Fuses for control-power transformers.
  - 3. Bimetallic-element overload relay.
  - 4. Indicating lights.
  - 5. Seal-in contact.
  - 6. Two convertible auxiliary contacts.
  - 7. Push buttons.
  - 8. Selector switches.
- B. Contactors: NEMA ICS 2, Class A, combination controller equipped for panelboard mounting and including the following accessories:
  - 1. Individual control-power transformers.
  - 2. Fuses for control-power transformers.
  - 3. Indicating lights.
  - 4. Seal-in contact.
  - 5. Convertible auxiliary contacts.
  - 6. Push buttons.
  - 7. Selector switches.
- C. Controller Disconnect Switches: Fused switch or Adjustable instantaneous-trip circuit breaker or integrally mounted or mounted adjacent to and interlocked with controller, as appropriate.
  - 1. Auxiliary Contacts: Integral with disconnect switches to de-energize external control-power source.
- D. Contactors in Main Bus: NEMA ICS 2, Class A, mechanically held general-purpose controller.
  - 1. Control-Power Source: Control-power transformer, with fused primary and secondary terminals, connected to main bus ahead of contactor connection.
  - 2. Control-Power Source: 120-V branch circuit.

## 2.8 ACCESSORY COMPONENTS AND FEATURES

- A. Furnish accessory set including tools and miscellaneous items required for overcurrent protective device test, inspection, maintenance, and operation.
- B. Furnish portable test set to test functions of solid-state trip devices without removal from panelboard.
- C. Fungus Proofing: Permanent fungicidal treatment for panelboard interior, including overcurrent protective devices and other components.

## PART 3 - EXECUTION

### 3.1 INSTALLATION

- A. Install panelboards and accessories according to NEMA PB 1.1.
- B. Comply with mounting and anchoring requirements specified in Division 26 Section "Vibration and Seismic Controls for Electrical Systems."
- C. Mount top of trim 6'6" above finished floor, unless otherwise indicated.
- D. Mount plumb and rigid without distortion of box. Mount recessed panelboards with fronts uniformly flush with wall finish.
- E. Install overcurrent protective devices and controllers.
  - 1. Set field-adjustable switches and circuit-breaker trip ranges.
- F. Install filler plates in unused spaces.
- G. Stub Three 3/4 inch empty conduits from panelboard into accessible ceiling space or space designated to be ceiling space in the future. Stub three 3/4 inch empty conduits into raised floor space or below slab not on grade.
- H. Identify field-installed conductors, interconnecting wiring, and components; provide warning signs as specified in Division 26 Section "Identification for Electrical Systems."
- I. Panelboard Nameplates: Label each panelboard with engraved metal or laminated-plastic nameplate mounted with corrosion-resistant screws.
- J. Ground equipment according to Division 26 Section "Grounding and Bonding for Electrical Systems."
- K. Connect wiring according to Division 26 Section "Low-Voltage Electrical Power Conductors and Cables."

### 3.2 FIELD QUALITY CONTROL

- A. Prepare for acceptance tests as follows:
  - 1. Test insulation resistance for each panelboard bus, component, connecting supply, feeder, and control circuit.
  - 2. Test continuity of each circuit.

B. Perform the following field tests and inspections and prepare test reports:

1. Perform each electrical test and visual and mechanical inspection stated in NETA ATS, Section 7.5 for switches and Section 7.6 for molded-case circuit breakers. Certify compliance with test parameters.
2. Correct malfunctioning units on-site, where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.

C. Load Balancing: After Substantial Completion, but not more than 60 days after Final Acceptance, measure load balancing and make circuit changes.

1. Measure as directed during period of normal system loading.
2. Perform load-balancing circuit changes outside normal occupancy/working schedule of the facility and at time directed. Avoid disrupting critical 24-hour services such as fax machines and on-line data processing, computing, transmitting, and receiving equipment.
3. After circuit changes, recheck loads during normal load period. Record all load readings before and after changes and submit test records.
4. Tolerance: Difference exceeding 20 percent between phase loads, within a panelboard, is not acceptable. Rebalance and recheck as necessary to meet this minimum requirement.

D. CLEANING

1. On completion of installation, inspect interior and exterior of panelboards. Remove paint splatters and other spots. Vacuum dirt and debris; do not use compressed air to assist in cleaning. Repair exposed surfaces to match original finish.

**END OF SECTION 26 24 16**