

## **SECTION 26 43 13 - TRANSIENT-VOLTAGE SURGE SUPPRESSION**

### **PART 1 - GENERAL**

#### **1.1 SUMMARY**

- A. This Section includes TVSSs for low-voltage power equipment.

#### **1.2 SUBMITTALS**

- A. Product Data: For each type of product indicated. Include rated capacities, operating weights, operating characteristics, furnished specialties, and accessories.
- B. Field quality-control test reports.
- C. Operation and Maintenance Data.

#### **1.3 QUALITY ASSURANCE**

- A. Source Limitations: Obtain suppression devices and accessories through one source from a single manufacturer.
- B. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- C. Comply with IEEE C62.41, "IEEE Guide for Surge Voltages in Low Voltage AC Power Circuits," and test devices according to IEEE C62.45, "IEEE Guide on Surge Testing for Equipment Connected to Low-Voltage AC Power Circuits."
- D. Comply with NEMA LS 1, "Low Voltage Surge Protection Devices."
- E. Comply with UL 1283, "Electromagnetic Interference Filters," and UL 1449, "Transient Voltage Surge Suppressors."

#### **1.4 PROJECT CONDITIONS**

- A. Service Conditions: Rate surge protection devices for continuous operation under the following conditions, unless otherwise indicated:
  - 1. Maximum Continuous Operating Voltage: Not less than 115 percent of nominal system operating voltage.
  - 2. Operating Temperature: 30 to 120 deg F (0 to 50 deg C).
  - 3. Humidity: 0 to 85 percent, noncondensing.
  - 4. Altitude: Less than 20,000 feet (6090 m) above sea level.

## 1.5 COORDINATION

- A. Coordinate location of field-mounted surge suppressors to allow adequate clearances for maintenance.

## PART 2 - PRODUCTS

### 2.1 MANUFACTURERS

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following or approved equal:
  - 1. Advanced Protection Technologies, Inc.
  - 2. Atlantic Scientific Corp.
  - 3. Current Technology, Inc.
  - 4. Cutler-Hammer, Inc.
  - 5. Entrelec, Inc.
  - 6. Innovative Technology, Inc.
  - 7. Intermatic, Inc.
  - 8. LEA International.
  - 9. Leviton Manufacturing Co. Inc.
  - 10. Liebert Corp.
  - 11. Northern Technologies.
  - 12. Siemens Energy & Automation.
  - 13. Square D Co.
  - 14. Sutton Designs, Inc.
  - 15. Transtector Systems, Inc.
  - 16. Tycor International, Inc.
  - 17. United Power, Inc.
  - 18. Zero Surge Inc.

### 2.2 SERVICE ENTRANCE SUPPRESSORS

- A. Surge Protection Device Description: Non-modular, sine-wave-tracking type with the following features and accessories:
  - 1. LED indicator lights for power and protection status.
  - 2. Audible alarm, with silencing switch, to indicate when protection has failed.
  - 3. Fuses, rated at 200-kA interrupting capacity.
  - 4. Integral disconnect switch.
  - 5. Redundant suppression circuits.
  - 6. Surge-event operations counter.
- B. Peak Single-Impulse Surge Current Rating: **[320] [240] [160]** kA per phase.
- C. Connection Means: Permanently wired.

- D. Protection modes and UL 1449 suppressed voltage rating for grounded wye circuits with voltages of 480Y/277 and 208Y/120, 3-phase, 4-wire circuits shall be as follows:
1. Line to Neutral: 800 V for 480Y/277 400 V for 208Y/120.
  2. Line to Ground: 800 V for 480Y/277 400 V for 208Y/120.
  3. Neutral to Ground: 800 V for 480Y/277 400 V for 208Y/120]
- E. Protection modes and UL 1449 suppressed voltage rating for 240/120-V, single-phase, 3-wire circuits shall be as follows:
1. Line to Neutral: 400 V.
  2. Line to Ground: 400 V.
  3. Neutral to Ground: 400 V.
- F. Protection modes and UL 1449 suppressed voltage rating for 240/120-V, 3-phase, 4-wire circuits with high leg shall be as follows:
1. Line to Neutral: 400 V, 800 V from high leg.
  2. Line to Ground: 400 V.
  3. Neutral to Ground: 400 V.
- G. Protection modes and UL 1449 suppressed voltage rating for voltages of 240 or 480, 3-phase, 3-wire, delta circuits shall be as follows:
1. Line to Line: 2000 V for 480 V 1000 V for 240 V.
  2. Line to Ground: 1500 V for 480 V 800 V for 240 V.

### 2.3 PANELBOARD SUPPRESSORS

- A. Surge Protection Device Description: Non-modular, sine-wave-tracking type with the following features and accessories:
1. LED indicator lights for power and protection status.
  2. Audible alarm, with silencing switch, to indicate when protection has failed.
  3. Fuses, rated at 200-kA interrupting capacity.
  4. Integral disconnect switch.
  5. Redundant suppression circuits.
  6. Surge-event operations counter.
- B. Peak Single-Impulse Surge Current Rating: [160] [120] [80] kA per phase.
- C. Protection modes and UL 1449 suppressed voltage rating for grounded wye circuits with voltages of 480Y/277 and 208Y/120, 3-phase, 4-wire circuits shall be as follows:
1. Line to Neutral: 800 V for 480Y/277 400 V for 208Y/120.
  2. Line to Ground: 800 V for 480Y/277 400 V for 208Y/120.
  3. Neutral to Ground: 800 V for 480Y/277 400 V for 208Y/120]

- D. Protection modes and UL 1449 suppressed voltage rating for 240/120-V, single-phase, 3-wire circuits shall be as follows:
  - 1. Line to Neutral: 400 V.
  - 2. Line to Ground: 400 V.
  - 3. Neutral to Ground: 400 V.
- E. Protection modes and UL 1449 suppressed voltage rating for 240/120-V, 3-phase, 4-wire circuits with high leg shall be as follows:
  - 1. Line to Neutral: 400 V, 800 V from high leg.
  - 2. Line to Ground: 400 V.
  - 3. Neutral to Ground: 400 V.
- F. Protection modes and UL 1449 suppressed voltage rating for voltages of 240 or 480, 3-phase, 3-wire, delta circuits shall be as follows:
  - 1. Line to Line: 2000 V for 480 V 1000 V for 240 V.
  - 2. Line to Ground: 1500 V for 480 V 800 V for 240 V.

## 2.4 ENCLOSURES

- A. NEMA 250, with type matching the enclosure of panel or device being protected.

## PART 3 - EXECUTION

### 3.1 INSTALLATION OF SURGE PROTECTION DEVICES

- A. Install devices at service entrance on load side, with ground lead bonded to service entrance ground.
- B. Install devices for panelboard and auxiliary panels with conductors or buses between suppressor and points of attachment as short and straight as possible. Do not exceed manufacturer's recommended lead length. Do not bond neutral and ground.
  - 1. Provide multipole, [30] [60] [100]-A circuit breaker as a dedicated disconnect for suppressor, unless otherwise indicated.

### 3.2 PLACING SYSTEM INTO SERVICE

- A. Do not energize or connect service entrance equipment panelboards control terminals [data terminals to their sources until surge protection devices are installed and connected.

### 3.3 CONNECTIONS

- A. Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. If manufacturer's torque values are not indicated, use those specified in UL 486A and UL 486B.

### 3.4 FIELD QUALITY CONTROL

- A. Testing: Perform the following field quality-control testing:
  - 1. After installing surge protective devices, but before electrical circuitry has been energized, test for compliance with requirements.
  - 2. Complete startup checks according to manufacturer's written instructions.
  - 3. Perform each visual and mechanical inspection and electrical test stated in NETA ATS, Section 7.19. Certify compliance with test parameters.
- B. Repair or replace malfunctioning units. Retest after repairs or replacements are made.
- C. Manufacturer's Field Service: Engage a factory-authorized service representative to inspect field-assembled components and equipment installation, including piping and electrical connections. Report results in writing.
  - 1. Verify that electrical wiring installation complies with manufacturer's installation requirements.

**END OF SECTION 26 43 13**